



The 41.0 is Coda's flagship Class A stereo amplifier. 56 high-bandwidth fifteen-ampere output devices provide high-current output into virtually any load with a frequency response reaching from 100kHz down to DC. The optional remote control allows input selection and bias control, and internal controls allow the 41.0 to be bridged into a high-current monoblock.

<ul style="list-style-type: none"> • 400 Watts into 8 Ohms • 800 Watts into 4 Ohms • >1000 Watts into 2 Ohms • Ultra high current non-bridged design • Fully discrete FET differential input stage • Vertical MOSFET Voltage gain stage • DC coupled to an ultra wideband bipolar output stage • Very high linear damping with minimal feedback • AC-coupled unbalanced input and true DC coupled balanced input • Double-sided gold plated circuit boards • 3.0kVA toroidal power transformer • Low-impedance power supply filter capacitor array • Graphite anodize aluminum and stainless steel finish • Power supply and Bias status indicators • 10 year warranty / 5 year transferrable • Designed, manufactured and assembled in the USA 	<p>Rated Power: 400W/ch Class AB into 8Ω 800W/ch Class AB into 4Ω 1600W bridged Class AB into 8Ω</p> <p>Frequency Response: DC to 100kHz @ -3dB</p> <p>Distortion: <.02% from 10Hz to 20kHz at rated power</p> <p>Gain: 26dB</p> <p>Maximum Current: >100 Amperes peak per channel</p> <p>Noise: -126dB</p> <p>Input Impedance: 50kΩ unbalanced 10kΩ balanced</p> <p>Output Impedance: .03Ω from 20Hz to 20kHz .06Ω bridged from 20Hz to 20kHz</p> <p>Power Supply: 3kVA toroidal power transformer. Dual independent rectification and 280,000uF of power supply filter capacitance</p> <p>Dimension: 18" W x 19" D x 7.75" H</p> <p>Weight : 110 lbs.</p>
--	---