



The 16.0 is Coda's flagship Class A stereo amplifier, sharing the design of the 40.5. Optimized for Class A operation, the 16.0 is better suited to low-impedance speaker systems where higher current capability yields superior performance. The optional remote control allows input selection and bias control, and internal controls allow the 16.0 to be bridged into a high-current monoblock.

- 150 Watts into 8 Ohms
- 300 Watts into 4 Ohms
- Precision Bias Class A operation to 100 Watts sliding to Class AB at higher output level
- Ultra high current non-bridged design
- Fully discrete FET differential input stage
- Vertical MOSFET Voltage Gain Stage
- DC coupled to an ultra wideband bipolar output stage
- Very high linear damping with minimal feedback
- AC-coupled unbalanced input and true DC coupled balanced input
- Double-sided gold plated circuit boards
- 3.0kVA toroidal power transformer
- Low-impedance power supply filter capacitor array
- Graphite anodized aluminum and stainless steel finish
- Power supply and Bias status indicators
- 10 year warranty / 5 year
- Designed, manufactured and assembled in the USA

Rated Power:	150W/ch Class AB into 8Ω (100W/ch Class AB into 8Ω) 300W/ch Class AB into 4Ω 600W bridged Class AB into 8Ω 1200W bridged Class AB into 4Ω
Frequency Response:	DC to 100kHz @ -3dB
Distortion:	<.02% from 10Hz to 20kHz at rated power
Gain:	26dB
Maximum Current:	>100 Amperes peak per channel
Noise:	-130dB
Input Impedance:	50kΩ unbalanced 10kΩ balanced
Output Impedance:	.03Ω from 20Hz to 20kHz .06Ω bridged from 20Hz to 20kHz
Power Supply:	3kVA toroidal power transformer. Dual independent rectification and 280,000uF of power supply filter capacitance
Dimension:	17.5" W x 19" D x 7.75" H
Weight :	110 lbs.