



- State-of-the-art, remote-controlled “separates” performance with the added benefit of balanced audio inputs for even greater audio quality.
- Pre-amplifier section derived from the Coda 05x design, utilizing the Burr-Brown digitally-controlled precision analog attenuator. Component upgrades include PRP audio resistors, Multicap capacitors and high speed rectifiers for the preamp power supply
- Coda CSX Precision Bias Class A/AB amplifier design with discrete FET differential input stage, MOSFET voltage gain DC coupled to an ultra wideband bipolar output stage.
- Low overall feedback
- Separate tape monitor and processor loops
- Stereo subwoofer output
- Wideband, fully-regulated power supply with EMI and RFI line filtering
- Double-sided gold plated circuit
- All anodized chassis
- 10 year warranty / 5 year transferable
- Designed, manufactured and assembled in the USA

Rated Power:	V3:	400W/ch Class A into 8Ω 800W/ch Class A into 4Ω
	V2:	250W/ch Class A into 8Ω 500W/ch Class A into 4Ω
	V1:	150W/ch Class A into 8Ω 300W/ch Class A into 4Ω
Frequency Response:	DC to 100kHz @ -3dB	
Distortion:	<.04% from 10Hz to 20kHz @ 400 Watts	
Gain:	26dB	
Maximum Current:	130 Amperes peak per channel	
Noise:	-130dB	
Input Impedance:	50kΩ balanced 1kΩ balanced	
Output Impedance:	.04Ω from 20Hz to 20kHz	
Power Supply:	3kVA toroidal power transformer. Dual independent rectification and 80,000uF of power supply filter capacitance	
Dimension:	17" W x 14" D x 5.5" H	
Weight :	55 lbs.	